

Other Tips & Tricks:

- With higher Volume & Fuzz set lower, the Bass BluesFuzz JR sounds like a small tube amp (Tight on Fat, Boost Off, Tone lower). Set Dry Low to taste.
- For the thickest and buzziest fuzz, use Boost On, Mid set low, Tone high, and Tight set to Fat....and crank the Fuzz!
- To set volumes, set Volume at 0, set Dry Low to balance with off, then add in fuzz Volume
- With Tight set on Tight, you might need to increase the amp's bass control.

amptweaker™
good tone comes from tweaking ...

Amptweaker, LLC *made in USA*
3482 Keith Bridge Rd, #345 www.amptweaker.com
Cumming, GA 30041 ©2017 Amptweaker, LLC



Thanks for buying a Bass BluesFuzz JR™ pedal, another Amptweaker™ product we designed with your advice. It shares the tones of the low gain Germanium BluesFuzz LTD, with extended lowend, and our special Dry Low knob. Keep the ideas coming!

James Brown
James Brown, Amp Engineer

Cool Ideas:

- True Bypass—with special input circuitry, works great with active pickups
- Tight switch lets YOU dial in the chunk
- Volume, Tone, & Fuzz with automatic bias tracking for better clean tones
- Low gain Germanium w/ Boost switch
- Mid EQ for critical mid frequencies
- Dry Low blends clean lowend back in!

How does the



work?

Volume—Master Volume of Fuzz, set for boost or balance with the bypassed levels

Tone—EQ, adjusts highs up and down to balance with lows

Fuzz—adjusts distortion, while adjusting bias for better clean

Boost SW—Boosts gain ~10dB for more Fuzz, or for using vintage pickups

Tight SW—Tight for aggressive, chunky attack Fat for a thicker, and 'buzzier' distortion tone

Tie-wrap holes—use to mount on 'hole' style pedalboards

Screw holes—use to mount on your pedalboard using screws or bolts

Output Jack—connect to the next pedal's input or amp

Mid EQ—Output EQ, up for more of an overdrive tone, down for heavier, hollow, scooped tones

Dry Low—Blends in clean lowend

True Bypass SW—disconnects all circuitry and directly connects Input jack to the Output Jack

DC Jack—use regulated 9V–18VDC supply, with (-)center pin...9V is the most distorted, 18V is cleaner, and louder—is better for clean boosting

Input Jack—from bass or previous effect. Disconnects battery when unplugged

Specs:

- Input impedance: 250K Ohm (with the effect on)
- Output Impedance: 1K Ohm (with the effect on)
- Current draw: 11mA at 9V, 15mA at 18V
- Adapter: 9-18VDC adapter w/5.5mm X 2.1mm positive barrel, center ground negative(-)
- Housing: 2mm Aluminum for strength with less weight
- Weight: 9 ounces
- Dimensions: 2.7"W X 4.65"D X 2"H