

STRAWBERRY RED OVERDRIVE DLX

BJFe Series | Overdrive Pedal



Specifications

Input impedance: 560K
Output impedance: 25K
Drive voltage: 9V to 18V
Current consumption: 11,7mA
S / N ratio: -90dB
Size: 61Wx113Dx31H mm (excluding protrusions)
66Wx113Dx46H mm (including protrusions)

Features

One Control STRAWBERRY RED OVERDRIVE DLX (SRODDLX) is the newest edition of our classic STRAWBERRY RED OVERDRIVE (SROD) that has been very popular with One Control users for its high-quality tones and superb dynamic response.

This new DLX six knob model gives you more control over your tones with finely tuned precision. The SRODDLX still retains the classic original circuit developed by Björn Juhl and One Control with an overdrive that transcends style and genre. To be able to interface with a wide variety of amplifiers and speakers, the DLX has a classic four knob tone circuit “stack” like many classic UK amplifiers - BASS, MIDDLE, TREBLE, and PRESENCE. With a single knob, this circuit can produce overdrive ranging from low bluesy tones to a hard and powerful overdrive as well as heavier distortions at the far-right side of the dial. With the DRIVE set to minimum, the SRODDLX can be used as a clean or treble booster style pedal. When the DRIVE knob is raised a bit more and the guitar volume knob lowered, the resulting clean sound can be rich with overtones and a thick responsive tone can be had, resembling older one knob tube amps. With the gain levels set higher, the SRODDLX still retains the characteristics of various guitars and amplifiers, never losing your core tone.

For many of us, the STRAWBERRY RED OVERDRIVE has been a favorite pedal for years.

Now we have it available in this six-knob dynamic and toneful version with standard and limited edition “Japonism” artwork.

Control

VOLUME: Adjusts the output volume.

DRIVE: Adjusts the overdrive gain. The gain increases clockwise.

TREBLE: Adjusts the overdrive tone centering on the high range. A shelving EQ of + 6dB @ 2KHz centered on 1kHz. The slope is from 700Kz to 6dB.

MID: Operates at ± 10 dB around 400 Hz.

BASS: Operates at ± 10 dB around 90 Hz.

PRESENCE: Adjusts the level of 4-7kHz.

DC INPUT: Connects a standard center minus 9V / 18V DC adapter. Supports 9-18V power supply. It can also be driven by a 9V battery.

* The LED turns off when the battery needs to be replaced. When driven by batteries, the INPUT terminal doubles as a power switch. When the main unit has batteries, unplug it from the input while using it.

Bjorn's Description:

STRAWBERRY RED OVERDRIVE DLX is SROD's philosophy of being able to push any amp and speaker combination, from low gain to medium gain overdrive, distortion, and even more distorted amps and other distortion pedals with any pickup. It was further strengthened. It's a muscle overdrive, but at the same time it can produce old sounds, and it's really versatile.

— Bjorn Juhl